


# Quick Reference Guide

Polycom SoundStation IP 7000





Item		Description
1	LCD Screen	Shows information about calls, messages, soft keys, time, date and other relevant data.
2	Soft Keys	Labels change automatically to identify their context- sensitive features.
3	Scroll Buttons	Allows the user to scroll through displayed information.
4	End Call Button	Ends a call.
5	Select Button	Allows the user to select a field of displayed data or menu option, or toggle a feature on or off.
6	Volume Buttons ◀)) ◀)	Adjusts the volume of the speaker and ringer.
7	Mute Button 🎍	Toggle the microphones off or on.
8	Keypad	Provides the digits, letters and special characters in context-sensitive applications.
9	Redial Button	Dials most recently dialed party.
10	Conference Button	Allows connection to multiple parties for conference calls.
11	Menu Button 🚃	Access phone features and customization.
12	Call Button	Initiates a call.

#### **Basic Features**

#### To Place a Call:

- Either:
  - Press the (3) button or the New Call soft key.
  - Enter the phone number or extension to dial, and then press the Send soft key.
    - -OR-
  - From the idle screen, enter the phone number or extension to dial, and then press the **Dial** soft key.

## To Place a Call from the Directory:

- Press the button and then select Features → Contact Directory.
- Press the and buttons to select the desired entry.
- Press the **Dial** soft key.

## To Place a Call from the Speed Dial List:

- Press the button—the Speed Dial Info screen displays
- Either:
  - Press the and buttons to select the desired entry.
     OR-
  - o Type the number of the Speed Dial Index of the contact, if known.
  - Press the **Dial** soft key.

#### To Answer a Call:

Press the button or the Answer soft key.

## To Reject a Call:

 Press the Reject soft key—the call will immediately be connected to the voice mail configured for the ringing extension.

#### To End a Call:

• Press the button or the **End Call** soft key.

#### To Redial the Last Call Placed:

Press the button—a call to the last number dialed is attempted.

#### To Mute a Call:

 Press the button—the call will be muted and the LCD screen will indicate that the call is muted.

#### To Place a Call on Hold:

Press the Hold soft key—the call will be placed on Hold, the LCD display on the
phone will change to indicate that the call is on Hold, and the hold icon will
display for the Line that is on Hold.

## To Resume a Call on Hold:

• Press the **Resume** soft key—the call will be resumed.

## **Basic Features (continued)**

## To Conference in a Second Party:

- Establish the call with the first party (either by calling the first party or after answering the call from the first party).
- Press the button or press the Confrnc soft key.
- Call the second party—wait until the call is answered.
- Press the **Confrnc** soft key—all parties are connected.

#### To Perform a Blind Transfer:

- Press the Trnsfer soft key.
- Press the Blind soft key.
- Dial the extension or phone number of the transfer recipient and then press the **Send** soft key—the call will immediately begin to ring on the recipient phone.

#### To Perform an Attended Transfer:

- Press the Trnsfer soft key.
- Dial the extension or phone number of the transfer recipient and then press the Send soft key—wait for the transfer recipient to answer the call and announce the caller.
- Press the **Trnsfer** soft key again—the call is connected to the transfer recipient.

## To Configure & Enable Always Forward:

- From the idle screen, press the **Forward** soft key.
- Press the and buttons to select Always, and then press the Select soft key.
- Enter the destination extension or phone number you want to forward all calls to
  in the Contact field, and then press the Enable soft key— the status line of the
  LCD display will begin to scroll and display a message, "Call Forward Enabled"
  and an animated call forward icon > will display next to the forwarded line.

# To Enable / Disable Do Not Disturb (DND):

- Press the button.
- Select Features → Do Not Disturb.
- Press the Select soft key—a message "(X) Do Not Disturb" will begin to scroll on the status line of the LCD screen, and a flashing icon X will appear next to the extension to indicate that DND mode is enabled.

#### To Park a Call:

- During an active call, dial #72—the system will respond with a prompt indicating which parking lot number to dial to retrieve the call (780x).
- <u>Listen</u> to the system prompt and <u>remember</u> which parking lot location the active call has been assigned.

## To Retrieve a Parked Call:

• Dial the parking lot location (**780x**)—the parked call will be connected with that phone.

## Voice Mail Quick Reference

When the phone receives a new voice mail message, a new message icon will appear next to the extension and the phone will play a stutter dial tone to indicate that the phone has new voice mail waiting.

#### To Listen to Voice Mail:

- Press the Messages soft key—a summary screen will indicate how many new messages have been received, and how many old messages are being saved.
- Press the **Connect** soft key—the phone will connect to the voice mail box.

#### To Access Voice Mail from a Different Internal Phone:

- Dial 7999—the system will prompt for an extension.
- Dial the extension—the system will prompt for a password.
- Dial the password—the system will prompt with the Voice Mail Main Menu.

#### **Voice Mail Main Menu:**

- 1 New Messages (or if no New Messages, Old Messages)
- 2 Change Folders
  - 0 New Messages
  - 1 Old Messages
  - 2 Work Messages
  - 3 Family Messages
  - 4 Friends Messages
  - # Cancel
- 3 Advanced Options (used only during message playback)
  - Return to Main Menu
- 0 Mailbox Options
  - 1 Record Unavailable Message
  - 2 Record Busy Message
  - 3 Record Name
  - 4 Manage Temporary Greeting
    - 1 Record Temporary Greeting
    - 2 Erase Temporary Greeting (available only if a Temporary Greeting is present)
  - 5 Change Password
  - \* Return to Main Menu
- \* Help
- # Exit Voice Mail

## Options During Playback (any folder):

- 3 Advanced Options
  - 1 Send Reply (available only if message was sent or forwarded from an internal extension)
  - 3 Hear Message Envelope
  - \* Return to Main Menu
- 4 Play Previous Message (available only if multiple messages present in current folder)
- 5 Repeat Current Message
- 6 Play Next Message (available only if multiple messages present in current folder)
- 7 Delete Current Message
- 8 Forward Message to Another Mailbox
- 9 Save Message in a Folder:
  - 0 New Messages
  - 1 Old Messages
  - 2 Work Messages
  - 3 Family Messages
  - 4 Friends Messages
  - # Cancel
- \* Rewind 3 Seconds
- # Skip Forward 3 Seconds

# Options After Recording a Message / Greeting:

- 1 Accept the Message / Greeting
- 2 Listen to the Message / Greeting
- 3 Re-record the Message / Greeting